

ECR/EPOS Technical Support

XEA PC LINK With SD CARD Guide

This guide is intended to cover the download and installation of the PC Link software for the XEA-217/207/307 and how to use the SD Card feature.

The SD Card feature allows the user to make program changes on the pc and transfer the changes to the till via the SD Card. A Backup feature is also provided to keep a program backup of the till.

The PC Link software can be downloaded from the following URL:

XEA-207

http://www.tradenet.sharp.co.uk/tech/download.asp?ID=110903

XEA-217

http://www.tradenet.sharp.co.uk/tech/download.asp?ID=110905

XEA-307

http://www.tradenet.sharp.co.uk/tech/download.asp?ID=110963

Please note the download is in .ZIP format and will need to be uncompressed before you can use it. (Please use Winzip or Winrar to uncompress).

Once the files have been uncompressed, locate the file PC-LINK_A217V.exe and run this file.

(If you want a shortcut on your desktop, right mouse click on the file and select "Send to > Desktop")



ECR/EPOS Technical Support

Loading data from SD card into PC Link

- 1) Insert your SD card into your SD card reader on your PC.
- 2) Select File > Export/Import
- 3) Select the Folder (Created on the till when performing backup)
- 4) Click Import
- 5) Select YES

Your backup on your SD will now be loaded into PC Link for editing.

Saving data from PC Link to SD Card

- 1) Insert your SD card into your SD card reader on your PC.
- 2) Select File > Export/Import
- 3) Select the Folder you want to Save the Data to (If you have not created a folder then click "New Folder" to create one)
- 4) Once the Folder is selected, Click on Export
- 5) Click Yes

Your Data will now have been saved to the SD card ready to be inserted into a till for import.

Save from Till to SD Card

- 1) Insert SD card into SD Card Reader in front of till.
- 2) Press Mode
- 3) Select 7 (SD Card Mode) then TL/NS
- 4) Select 3 (Folder Control) then TL/NS
- 5) Select 1 (Create Folder)
- 6) Enter Text of Folder (eq. Name of your business)
- 7) Press TL/NS
- 8) Press TL/NS (On OK
- 9) Select 2 (Select Folder)
- 10) Use arrow keys to highlight the folder in which you would like to save the data and then press TL/NS
- 11) Press ESC
- 12) Select 1 (Saving) Press TL/NS
- 13) Select 1 (Save) Press TL/NS)
- 14) Select 4 (ALL Program) Press TL/NS
- 15) Press TL/NS to confirm OK
- 16) Use ESC key to return to REG mode



ECR/EPOS Technical Support

Load from SD Card to Till

- 1) Insert CD Card into Till
- 2) Press Mode
- 3) Select 7 (SD Card Mode) then TL/NS
- 4) Select 3 (Folder Control) then TL/NS
- 5) Select 2 (Select Folder)
- 6) Use arrow keys to highlight the correct folder then TL/NS
- 7) Press ESC
- 8) Select 2 (Loading) then TL/NS
- 9) Select 2 (All Program)
- 10) Select 1 (OK) then TL/NS

Once complete use the ESC key to return to normal registration, the program will now be loaded.